



Email : sales@laboratoryinstrumentindia.com

Product Name :
Solar Cell Trainer Modules

Product Code :
LBNY-0002-620055



Description :

Solar Cell Trainer Modules

Technical Specification :

Solar Cell Trainer

The Solar Cell Trainer is an easy and self-contained trainer designed for learning the basic configuration and characteristics of a solar cell.

Through the use of different irradiations for various load units, students study the photoelectric effect of solar cells and plot the current-voltage curve as well as charging / discharging curves.

Solar Cell Modules

1 pcs of monocrystalline silicon solar cell.

Each unit : solar cell

Open circuit voltage (Voc): 49.75V DC ±2V

Short circuit current (Isc) : 13.93A ±1A

Maximum load voltage (Vpm): 41.8V DC ±2V

Maximum load current (Ipmp) : 13.04A ±1A

Maximum power (Ppm) : 545W A ±25W

Efficiency (Eff) : Not less than 20%

Adjustable Angle (0-90)degree dua axis

Dimmer

Adjust the brightness of halogen lamp :

Input voltage 110VAC or 230VAC

Output voltage 0-230V

Light Source

Halogen lamp 230V/100W

Beam angle 90° variable

Digital Multimeter x 2

DC Voltage : 400mV, 4V, 40V, auto range

Input resistance ? 10M?

AC Voltage : 400mV, 4V, 40V, auto range

Input resistance ? 10M?

DC Current : 400?A, 400mA,10A, push button selector switch

10A Range : 10A/250V fuse protected

mA/ A Ranges : 0.5A / 250V fuse protected

AC Current : 400?A, 400mA,10A, push button selector switch

10A Range : 10A/250V fuse protected mA/?A

Ranges : 0.5A/250V fuse protected ?

Resistance : 400?, 4K?, 40K?, 4M?, 40M?, auto range

Diode test : 0~1.5V

Continuity : Buzzer for the measured resistance Display : 3 ¾ digit LCD, max. indication 3999

Energy Storage

NiMH rechargeable battery 1.2V/80mAh

Super capacitor 10F/2.7V

Load

DC motor : 0.5V~6V,10mA

Light bulb: 1.1V, 300mA

Potentiometer : 100?, 10-turn

Inverter

Input voltage : 2VDC

Output :

Modified sine wave 1Vpp 50/60Hz

Square wave 2Vpp 50/60Hz

Power Supply

Input voltage 110/220 VAC

Output voltage 15VDC

DAQ with Sofware

Channel 1 and 2 : max. input voltage ±5V

Channel 3 and 4 : max. input current 1A

System Requirements

List of Experiments

Measuring the irradiation of various light sources

Energy conversion of solar cells

Diode characteristic of a solar cell

Effect of light-sensing area on the open-circuit voltage of solar cell

Effect of light-sensing area on the short-circuit current of solar cell

Effect of irradiation on open-circuit voltage and short-circuit current of solar cells

Relationship between the angle of irradiation and the short- circuit current of solar cell

Open-circuit voltage and short-circuit current of solar cells connected in series-shading
Open-circuit voltage and short-circuit current of solar cells connected in parallel-shading
I-V curve of solar cells
Conversion efficiency and Maximum Power Point(MPP)
Simulating a daily course of sunlight
Charging a capacitor with solar cells
Capacitor discharging
Constructing a solar power island system
Inverter

Optional

8 Solar Power Meter

Display : 3 ½ digit LCD, max indication 1999 2 2 2.

Measuring range : 2000 W/m , 634 Btu/(ft x h) 2 2 3.

Resolution : 0.1 W/m , 0.1 Btu/(ft x h) 2 2 4.

Accuracy : ±10 W/m , ±3 Btu/(ft x h)

Sampling rate : 2 Hz.

Accessories:

Test leads : 1 set

Experiment manual

Instructor's manual

Basic solar power meter (GES-18002)

Operating with DAQ 2

Measuring range 10~1200W/m

25% Shading plate

50% Shading plate

75% Shading plate

100% Shading plate.



Laboratory Instrument India